

10W R80 MOTION SENSOR LED GLOBE



IXL Tastic Motion Sensor LED Globe provides automatic switching on and off, saves energy and increases your level of comfort.

How It Works:

Tastic Motion Sensor LED Globe will dim 10 seconds before switching off, and will resume at full brightness once reactivated by movement. Without any movement the motion sensor LED light will gradually dim to off within a period of 2 minutes. Detection range is between 3 – 5 metres from the globe, it functions through screens and shower doors.

The motion sensor function can be switched off from the LED light globe. Alternatively you can switch off the light switch on the wall plate. This LED motion sensor light globe is applicable to the centre LED light globe only, not including the heat lamp or exhaust fan.

This LED motion sensor light globe has been specifically developed to fit the IXL Tastic Mirage and other Tastic 3 in 1 products (except Tastic Original and Tastic Prime).

PRODUCT SPECIFICATIONS

Input Power (W)	10
Rated Voltage	220-240V
Colour Temperature (Kelvins)	4000K Cool White
Luminous Flux (lm)	900
Luminous Efficacy (lm/W)	>80
Colour Rendering Index (CRI)	>80
Beam Angle	110°
Rated Life (Hrs)	25,000
Switching Cycles	15,000
Instant Light	Yes
Lamp Base	E27
Dimension (mm) W x H	80 x 115
Detection Area	3 - 5 metres



No Mercury



Energy Saving



Suitable for
wet/steamy areas



Beam Angle
110°

Whilst every effort is made to provide current information at the time this brochure was produced, continuing product improvements mean the enclosed specifications, images and literature may differ from what is actually available.



Home

THE HOME OF PREMIUM BRANDS

AUSTRALIA
1K Marine Parade, Abbotsford VIC 3067

T: 1300 727 421
E: orders@ixl.com.au
W: ixlappliances.com.au

NEW ZEALAND

T: 0800 727 421
E: orders@ixl.com.au
W: ixlappliances.co.nz

